

Mobile phone jammer

MGT-02

Bands GSM / DCS / UMTS / CDMA



SPECIFICATIONS

- Adjustable output power from 2 to 8 watts, range 20 to 50 m
- Range diameter can be changed via the remote control
- 4 frequency bands jammed (GSM,DCS, UMTS 3G, CDMA)
- Working without time limit

External antennas.
 Continuous jamming
 Does not interfere with other radio communication devices (ex : DECT phones, talkie walkie)
 Easy installation – wall mounted
 Remote control provided

APPLICATIONS

Continuous mobile phone jamming

- Restricted areas
- Conference rooms
- Exam rooms
- Church, temple, mosque
- Theaters
- Concert Hall
- Cinemas

CHARACTERISTICS

4 Bandes brouillées	Frequency bands jammed
CDMA	870 -880 MHz
GSM	925 -960 MHz
DCS	1 805 -1 880 MHz
UMTS, 3G	2 110 -2 170MHz
Frequency accuracy	+/-20kHz
Range	20 to 50 meters @ -75dBm 70 meters in open space
Adjustable output power	2 to 8 watts
Power supply	AC adapter : Input : AC 220V / output : DC 5V, 3A

PRODUCT INFORMATION

Dimensions W x H x P	190 x 170 x 50 mm (aluminium)
Weight	1,6 kg (with AC adapter)
Operating temperature	0° / +70°C
Warranty	1 year



MAGNUM TELECOM
 1, rue du Lavoir
 38590 St Etienne de St Geoirs
 France

Tél : + 33 476 31 34 92
 GSM : + 33 607 69 11 86
info@magnumtelecom.com