



Mobile phone jammer

MGT-04GPS

GSM / DCS / UMTS / GPS



MAGNUM TELECOM
 1, rue du Lavoir
 38590 St Etienne de St Geoirs
 France

Tél : + 33 476 31 34 92
 GSM : + 33 607 69 11 86
info@magnumtelecom.com

APPLICATIONS

Continuous mobile phone jamming

Restricted areas

Conference rooms

Exam rooms

Chuch, temple, mosque

Theaters

Concert Hall

Cinemas

SPECIFICATIONS

- Adjustable output power 0 to 12 watts (potentiometers)
- Adjustable range 0 to 80 meters
- 4 frequency bands jammed (GSM, DCS, UMTS/3G, GPS)
- Working without time limit

External antennas.

Continuous jamming

Does not interfere with other radio communication devices (ex: DECT phones, talkie walkies, etc)

Easy installation – wall mounted

ON/OFF remote control provided

CHARACTERISTICS

GSM	925 -960 MHz
DCS	1805 -1880 MHz
UMTS, 3G	2110 -2170 MHz
GPS	1400 – 1600 MHz
Frequency accuracy	+/-20kHz
Range	0 to 80 meters @ -75dBm 100 meters in open space
Adjustable output power	0 to 12 watts
Power supply	Input : AC 110-220V / output : DC 5V, 3A

PRODUCT INFORMATION

GSM	925 -960 MHz
DCS	1805 -1880 MHz
UMTS, 3G	2110 -2170 MHz
GPS	1400 – 1600 MHz